

C-Band Hub-mount SSPB



50W to 250W $SSPB-2000C^{TM}$ series

Features

- Converts L-Band to C-Band (see table A)
- Integrated amplifier with an output power of 50W to 250W (see table A)
- · Phase-locked oscillator to external 10MHz reference
- High linearity (low intermodulation products)
- Weatherproof package
- Remote Monitor & Control
- Protection against thermal runaway and out-of-lock conditions
- Output sample monitoring port
- Field Replaceable Power Supply
- Built-in Harmonic Filter
- Compact packaging
- CE Marking

Overview

The SSPB-2000CTM series are hub-mount up-converter transmitters, operating in the C-Band. The SSPB-2000CTM is an integrated unit, complete with power supply, phase-locked oscillator, mixer, filter and cooling mechanism. Intended for outdoor operation, the SSPB-2000CTM provides the utmost in convenience and efficiency. They are the smallest fully integrated units on the market today. Other SSPBs are also available for diverse powers or for operation at other up-link frequencies.

The design of these units is based on Advantech AMT™ industry proven reliable solid-state high power amplifiers. Built-in design features and assembly methods incorporated with efficient combining techniques result in an amplifier with exceptional linearity and operating efficiency. The use of high efficiency power supply and conservative thermal designs contribute to the trouble-free operation of the amplifier.


Built-in microprocessor controller provides the capability for serial port interfaces (RS232/485) for remote monitoring and control.

Application

The SSPB-2000CTM series convert an L-Band signal to the C-band frequency (see table A). Designed for C-Band satellite up-link applications, the SSPB C series are available in output power from 10W to 1000W. For higher power Advantech provides phase-combined systems. The SSPB-2000CTM series are fully integrated units with up to 250W output power designed for mounting outdoors, near the hub of an antenna.

Redundancy

With the addition of the appropriate waveguide and switch kit, The SSPB-2000C series converters can be easily converted for the operation in a redundant configuration with full remote Monitor and Control capability of the redundant system via serial interface.






Table A

Band	RF Band (GHz)	IF Band (MHz)	Output Power (W)	LO (GH z)
CL	4.400 - 5.000	950 – 1550	60 - 200	3.450
CP	6.425 - 6.725	1025 – 1325	50 - 200	5.400
CI	6.725 - 7.025	1225 – 1525	50 - 200	5.500
CR	5.725 - 6.025	950 – 1450	60 - 250	4.775
CS	5.850 - 6.425	950 – 1525	60 - 250	4.900
CX	5.850 - 6.725	950 – 1825	50 - 200	7.675

*Other frequency sub-bands are available. Please consult factory.

Options

- Internal High Stability 10 MHz Reference
- Redundant system
- Remote M&C panel (Ethernet port optional)

Accessories

- Redundancy Kit
- Mounting Frame



C-Band Hub-mount SSPB

	O-Da	iiu iiu	D-IIIO	unit O	ט וכ					
Technical Specifications	50W	60W	80W	100W	125W	150W	200W	250W		
Electrical Characteristics		1								
Availability in this series										
CS, CR	V	√	V	V	V	V	V	√		
CL	V	1	V	V	V	V	V	V		
CX, CI, CP	V	V	V	V	V	V	V	√		
Output power (P _{SAT}) (dBm)	+47	+48	+49	+50	+51	+52	+53	+54		
Output power (P1dB) min. (dBm)	+46	+47	+48	+49	+50	+51	+52	+53		
Conversion gain @ maximum	07 JD	00 -ID	00 -ID	70 JD	74 JD	70 JD	70 JD	74 -10		
setting at ambient temperature	67 dB	68 dB	69 dB	70 dB	71 dB	72 dB	73 dB	74 dB		
Gain adjustment range	20 dB									
Input/Output frequency range	See table A on front page									
Frequency sense	Non-inverting except for CX band (5.85 GHz – 6.725 GHz)									
Max input power without damage	+10 dBm	0 dBm								
Gain flatness	±2.0 dB, max over full band, 0.3 dB/10 MHz at 25°C									
Gain variation over temperature	±1.5 dB over full operating range									
Gain variation over 24 hours	±0.25 dB max at constant temperature & drive level									
Input return loss	18 dB									
Output return loss	19 dB									
Noise power density	-70 dBm/Hz, max in TX band -140 dBm/Hz, max in RX band									
Spurious at rated power	-60 dBc, max									
Harmonics at rated power	-70 dBc, max									
AM/PM conversion at rated power										
Third order IMD (2 tones) -26 dBc, max at 3 dB back-off from P1 dB										
Local Oscillator frequency (LO) See table A on front page										
LO leakage	-20 dBm		<u> </u>							
Phase noise	-50 dBc/Hz at 10Hz -75 dBc/Hz at 1000Hz -95 dBc/Hz at 100 kHz -65 dBc/Hz at 100Hz -85 dBc/Hz at 1 MHz -105 dBc/Hz at 1 MHz									
Group delay: (over any 40 MHz)	Linear 0.02 ns /MHz, max Parabolic 0.003 ns/MHz², max Ripple 1 nsec p-p, max									
Reference (auto-switching)	Trippie		1 11366	р-р, шах						
Note: In case external reference is	not provide	ed, the unit	will automa	atically swi	tch to inter	nal referenc	ce. For 1:1			
redundant operation, internal 10Mh										
Reference frequency	10 MHz									
Reference frequency phase noise	-115 dBc/Hz at 10 Hz -150 dBc/Hz at 10 kHz									
, ,,	-135 dBc/Hz at 100 Hz -160 dBc/Hz at 100 kHz -148 dBc/Hz at 1000 Hz									
Reference frequency level	0 dBm ± 5 dB									
Power Requirements										
AC input voltage	110 /220	VAC Auto i	anging (47	'-63 Hz)						
Power consumption (nom.) (W)	400W	600W	800W	900W	1000W	1200W	1300W	1500V		
Mechanical Characteristics										
Dimensions (L x W x H)	19.38"x 9	.80" x 9.20	" (49.22 x 2	25.40 x 23.	36 cm)					
Weight				(20 kg)	,		48.50 lb	s (22 kg)		
Interfaces: RF input N Ty Relay port MS3	pe (Female 112E12-10 102R16-10	P RS-232	dancy 2	MS3112E ² MS3112E MS3112E	10-6P C	Foutput C L series – (ntact (for		
Environmental Conditions										
Temperature: Operating Storage	-30°C to +55°C; Option 1: -40°C to +55°C; option 2: -50°C to +50°C									
	-55°C to +85°C									
Humidity	100%, condensing									
Altitude	10,000' AMSL, de-rated 2°C/1,000' from AMSL									

NORTH AMERICA USA

Tel: +1 703 659 9796 Fax: +1 703 635 2212 info.usa@advantechwireless.com

CANADA

Tel: +1 514 420 0045 Fax: +1 514 420 0073 info.canada@advantechwireless.com

EUROPE UNITED KINGDOM

Tel: +44 1480 357 600 Fax: +44 1480 357 601 info.uk@advantechwireless.com

RUSSIA & CIS

Tel: +7 495 971 59 18 info.russia@advantechwireless.com

INDIA

Tel: +91 33 2415 5922 info.india@advantechwireless.com

SOUTH AMERICA

Tel: +1 514 420 0045 Fax: +1 514 420 0073 info.latam@advantechwireless.com

BRAZIL

Tel: +55 11 3054 5701 Fax: +55 11 3054 5701 info.brazil@advantechwireless.com An ISO 9001: 2008 Company



Ref.: PB-SSPB-C-50-250-13150